

TEST BUS ARCHITECTURE FOR EMBEDDED RAM AND METHOD OF OPERATING  
SAME

Jeffrey Lukanc

FIELD OF THE INVENTION

[0001] The present invention relates to a test bus that provides test capability to integrated random access memories (RAMs) and register files.

DISCUSSION OF RELATED ART

[0002] Conventional integrated circuit chips typically include random access memory (RAM) that should be tested to ensure that the RAM is functional (i.e., free of defects). Relatively large RAMs (i.e., 2Mb or larger) typically have a dedicated built-in self test (BIST) unit, which writes a predetermined bit pattern to the RAM. The contents of the RAM are then read and compared with the predetermined bit pattern to determine whether the RAM includes any defective memory cells. Because of the overhead associated with the BIST circuitry, this technique is only used for relatively large RAMs. Moreover, because BIST circuitry only provides a predetermined bit pattern for testing the RAM, the testing of the RAM may be inadequate because of a limited bit pattern. Furthermore, stress tests, in which the operating speed of the RAM is tested, cannot be readily performed using BIST circuitry.

[0003] Smaller RAMs, such as register files, are typically difficult to test. Providing a separate BIST circuit to test each of these small RAMs is impractical, as the overhead associated with the BIST circuitry would result in an undesirably large circuit layout area. In addition, because the smaller RAMs are typically embedded in a logic system (i.e., an ethernet system or an ATM system), it can be difficult to provide the

[illegible][illegible]

	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99
0	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99

	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99
0	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99

[illegible]

	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99
0	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99

the test data values to the RAM/register blocks. Subsequently, the test data values are read from the RAM/register blocks by individually accessing the RAM/register blocks via the test bus and the test modules. The test modules are assigned unique addresses, thereby enabling the RAM/register blocks to be addressed during the read operations.

[0008] In accordance with another embodiment of the present invention, a switching structure is provided to enable the same set of pads to be used for the test bus during the test mode, and for other system signals during normal operation. This switching structure can be controlled by a tap state of a JTAG controller located on the chip.

[0009] During the test mode, the signals on the test bus are operated in response to a test clock signal, and the RAM/register blocks are operated in response to an independent system clock signal. By independently adjusting the various edges of the test clock signal and the system clock signal, stress testing can be performed on the RAM/register blocks.

[0010] The present invention will be more fully understood in view of the following description and drawings.

#### BRIEF DESCRIPTION OF THE DRAWINGS

[0011] Fig. 1 is a block diagram of a portion of a chip having a test bus in accordance with one embodiment of the present invention.

[0012] Fig. 2 is a block diagram of selected RAM/register blocks, corresponding test modules, and the test bus of Fig. 1.

[0013] Fig. 3 is a block diagram of a dual-port RAM/register block having one read port and one write port in accordance with one embodiment of the present invention.

[0014] Fig. 4 is a block diagram of a dual-port RAM/register block having two read ports and two write ports in accordance with one embodiment of the present invention.

[0015] Fig. 5 is a circuit diagram of a test module for the RAM/register block of Fig. 3 in accordance with one embodiment of the invention.

[0016] Fig. 6 is a circuit diagram of a test module for the RAM/register block of Fig. 4 in accordance with one embodiment of the invention.

#### DETAILED DESCRIPTION

[0017] Fig. 1 is a block diagram of a portion of an integrated circuit chip 100 having a test bus 200 in accordance with one embodiment of the present invention. The illustrated portion of chip 100 includes pads 1-22, JTAG controller 101, switching structure 102, inverter 103, test bus 200, embedded RAM/register blocks 201-209 and test modules 211-219. Although chip 100 includes many other elements, such as additional pads, interconnect structures, logic and memory, these additional elements are not shown for purposes of clarity. Moreover, although only nine RAM/register blocks are shown in the present example, it is understood that chip 200 can include many additional RAM/register blocks in other embodiments. In general, each of embedded RAM/register blocks 201-209 is a relatively small memory, having a capacity of about 4 Kb or less. Memories of this capacity are typically considered too small to efficiently include their own dedicated BIST circuitry. In other embodiments one or more of RAM/register blocks 201-209 are relatively large memories, which may have included their own dedicated BIST circuitry in prior art chips.

[0018] Switching structure 102 is controlled by a tap signal provided by JTAG controller 101. During normal operation of chip

100, JTAG controller 101 provides a logic low signal to switching structure 102. Under these conditions, inverter 103 provides a logic high signal to the upper set of switches in switching structure 102, thereby causing these switches to close.

Conversely, the lower set of switches in switching structure 102 receive a logic low signal, thereby causing these switches to open. As a result, pads 1-22 are isolated from test bus 200, and are coupled to predetermined circuitry (not shown) on chip 100.

[0019] However, during testing of chip 100, JTAG controller 101 is configured to provide a logic high signal to switching structure 102. In the described embodiment, one of the optional tap signals provided by JTAG controller 101 is used to provide the control signal to switching structure 102. Under these conditions, inverter 103 provides a logic low signal to the upper set of switches in switching structure 102, thereby causing these switches to open. Conversely, the lower set of switches in switching structure 102 receive a logic high signal, thereby causing these switches to close. As a result, pads 1-22 are connected to test bus 200, and are isolated from the predetermined circuitry. At this time, pads 1-22 are connected to test modules 211-219. Using switching structure 102 and JTAG controller 101 to provide the connections between pads 1-22 and test bus 200 advantageously reduces the pin count of chip 100, because additional pads are not required to access the test bus 200.

[0020] Test bus 200 is a versatile and efficient 22-signal bus that is coupled to each RAM/register block of chip 100 (through a corresponding test module). In the examples described below, test bus 200 supports a dual-port memory having two read/write ports. However, it is understood that test bus 200 is capable of supporting memories with any number of read/write ports.

**[0021]** Fig. 2 is a block diagram that illustrates RAM/register blocks 201-202, corresponding test modules 211-212, and test bus 200 in more detail. In the described embodiment, RAM/register block 201 is a dual-port RAM that is 128 words deep and 32 bits wide. RAM/register block 201 has one write port and one read port, which are controlled independent of one another. Separate clock input terminals are provided for the read port and the write port, thereby allowing the two ports to run asynchronously from each other. In the described examples, each of the clock input terminals is connected to receive a system clock signal. As a result, RAM/register block 201 operates in response to the system clock signals during the test mode. In the described embodiment, the core of RAM/register block 201 has a latch-based design, which uses conventional static random access memory (SRAM) cells. RAM/register block 201 is byte-write enabled, such that 8-bit bytes can be written to the write port of RAM/register block 201.

**[0022]** RAM/register block 201 receives the following input signals during normal operation of chip 100: write address signal A[6:0], read address signal B[6:0], data input signal DIN[31:0], byte-write enable signal WE[3:0], write clock signal CKA, read clock signal CKB and RAM enable signal RE. The write input signals A[6:0], DIN[31:0] and WE[3:0] are synchronous with the write clock signal CKA. The read input signal B[6:0] is synchronous with the read clock signal CKB. The output signals DOUT[31:0] provided by RAM 201 are asynchronous. RAM/register block 201 is designed to operate in response to clock signals (CKA and CKB) having frequencies of up to 266 MHz.

**[0023]** Fig. 3 illustrates RAM/register block 201 in more detail. As described in more detail below, test module 211 asserts a t\_mode signal during the test mode. The t\_mode signal is received by RAM/register block 201 as the signal, test\_mode.

Within RAM/register block 201, the test\_mode signal controls a set of multiplexers 221. When the test\_mode signal is de-asserted low, the system input signals A[6:0], B[6:0], DIN[31:0], and WE[3:0] are provided to control the RAM core 201C.

Conversely, when the test\_mode signal is asserted high, the test signals ta[6:0], tb[6:0], tdin[31:0] and twe[3:0] from test module 211 are provided to control RAM core 201C. The test signals ta[6:0], tb[6:0], tdin[31:0] and twe[3:0] are described in more detail below.

**[0024]** Returning now to Fig. 2, RAM/register block 202 is a dual-port RAM that is 32 words deep and 32 bits wide.

**[0025]** RAM/register block 202 has two independent read/write ports. Separate clock input terminals are provided for the first read/write port and the second read/write port, thereby allowing the two ports to run asynchronously from each other. In the described examples, each of the clock input terminals is connected to receive a system clock signal. As a result, RAM/register block 202 operates in response to the system clock signals during the test mode. In the described embodiment, the core of RAM/register block 202 has a latch-based design, which uses conventional SRAM cells. RAM/register block 202 is byte-write enabled, such that 8-bit bytes can be written to the write ports of RAM/register block 202.

**[0026]** RAM/register block 201 receives the following input signals during normal operation of chip 100: first port read/write address signal A[6:0], second port read/write address signal B[6:0], first port data input signal DINA[31:0], second port data input signal DINB[31:0], first port byte-write enable signal WEA[3:0], second port byte-write enable signal WEB[3:0], first port clock signal CKA, second port clock signal CKB and RAM enable signal RE. The first port input signals A[6:0], DINA[31:0] and WEA[3:0] are synchronous with the first port clock

signal CKA. The second port input signals B[6:0], DINB[31:0] and WEB[3:0] are synchronous with the second port clock signal CKB. The first port output signals DOUTA[31:0] and the second port output signals DOUTB[31:0] provided by RAM/register block 202 are asynchronous. RAM/register block 202 is designed to operate in response to clock signals (CKA and CKB) having frequencies of up to 100 MHz.

[0027] Fig. 4 illustrates RAM/register block 202 in more detail. As described in more detail below, test module 212 asserts a t\_mode signal during the test mode. The t\_mode signal is received by RAM/register block 202 as the signal, test\_mode. Within RAM/register block 202, the test\_mode signal controls a set of multiplexers 222. When the test\_mode signal is de-asserted low, the system input signals A[6:0], B[6:0], DINA[31:0], DINB[31:0], WEA[3:0] and WEB[3:0] are provided to control the RAM core 202C. Conversely, when the test\_mode signal is asserted high, the test signals ta[6:0], tb[6:0], tdina[31:0], tdinb[31:0], twea[3:0] and tweb[3:0] from test module 212 are provided to control RAM core 202C. The test signals ta[6:0], tb[6:0], tdina[31:0], tdinb[31:0], twea[3:0] and tweb[3:0] are described in more detail below.

[0028] Although RAM/register blocks 201-202 have the characteristics described above in the present embodiment, it is understood that RAM/register blocks 201-202 can have other characteristics in other embodiments of the present invention.

[0029] RAM/register blocks 201 and 202 are coupled to test bus 220 by test modules 211 and 212, respectively. Test bus 220 is a 22-bit bus that carries an 8-bit test bus address/data input signal tb\_ad[7:0], a 3-bit test bus command signal tb\_cmd[2:0], a 2-bit test bus byte-enable select signal tb\_be\_sel[1:0], a test bus clock signal tb\_clk, and an 8-bit test bus data output signal tb\_data[7:0].

	1970	1971	1972	1973	1974	1975	1976	1977	1978	1979	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2
--	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	---

[illegible][illegible]

		low.
ram_id[3:0]	Internal input	Unique 4-bit assigned address for each RAM.

[0031] A single command and control bus tb\_cmd[2:0] is provided for testing all RAMs. There are 8 instructions passed via the 3-bit command bus tb\_cmd[2:0]. These instructions are summarized below in Table 2.

TABLE 2  
Command Bus Instruction Decode

TB_CMD[2:0]	FUNCTION	DESCRIPTION
000	NOP	Normal chip operation mode (test mode is in idle)
001	ld_sel_add	Select a RAM (or RAM port) address (only used for reads)
010	ld_addr_a	Latch the address port (port A of all RAMs)
011	ld_addr_b	Latch the address for port-B (used for dual-port RAMs)
100	wr_a	Perform a write operation to all RAMs (through port A)
101	wr_b	Perform a write operation to port B of dual port RAMs
110	rd_a	Perform a read operation from port A of dual port RAM
111	rd_b	Perform a read operation from port B of a RAM

[0032] During the test operation, test signals are transmitted between test module 211 and RAM 201. The signals between test module 211 and RAM 201 are defined below in Table 3.

Signal	Type	Description
t_addr_a[7:0]	Output	Test mode address A
t_addr_b[7:0]	Output	Test mode address B
t_din[7:0]	Output	Test mode write data in to RAM
t_we[3:0]	Output	Test mode byte enable for write and read
t_mode	Output	Test mode control signal
t_dout[31:0]	Input	Test mode read data out from selected RAM

TABLE 4

Signal	Type	Description
t_addr_a[7:0]	Output	Test mode address A
t_addr_b[7:0]	Output	Test mode address B
t_din[7:0]	Output	Test mode write data in to RAM
t_wea[3:0]	Output	Test mode byte enable for write and read port A
t_web[3:0]	Output	Test mode byte enable for write and read port B
t_mode	Output	Test mode control signal
t_douta[31:0]	Input	Test mode read data out from selected RAM, port A
t_doutb[31:0]	Input	Test mode read data out from

		selected RAM, port B
--	--	----------------------

**[0034]** In the described example, the ram\_id[3:0] address of test module 211 (and RAM/register block 201) is selected to be 0000, and the ram\_id[3:0] address of test module 212 (and RAM/register block 202) is selected to be 0001. These addresses are hardwired within the test modules using non-volatile memory, such as fuses, or simply bits tied to logic high or logic low through supply connections. Although not described in detail herein, each of test modules 213-219 is also assigned a unique address.

**[0035]** Fig. 5 is a circuit diagram of test module 211 in accordance with one embodiment of the invention. Test module 211 includes logical AND gates 301-306, logical OR gate 310, D-type flip-flops 311-313, decoder 315, comparator 316, tri-state buffer 321 and 4-to-1 multiplexer 331.

**[0036]** Fig. 6 is a circuit diagram of test module 212 in accordance with one embodiment of the invention. Test module 212 includes logical AND gates 401-409, logical OR gate 410, D-type flip-flops 411-413, decoder 415, comparator 416, tri-state buffers 421-422 and 4-to-1 multiplexers 431-432.

**[0037]** RAM/register blocks 201 and 202 are tested as follows. Although not described in detail below, it is understood that RAM/register blocks 203-209 are tested at the same time and in the same manner as RAM/register blocks 201 and 202. To initiate the test mode, the test bus command signal tb\_cmd[2:0] is set to a value of "010", while the test bus clock tb\_clk has a logic low value. The input terminals of OR gates 310 and 410 are coupled to receive the test bus command signals tb\_cmd[2:0]. These OR gates 310 and 410 provide logic high t\_mode signals in response to the "010" value of the tb\_cmd[2:0] signals. As illustrated in Table 2, at least one of the tb\_cmd[2:0] signals has a logic high

value for each instruction provided during the test mode. Thus, during the test mode, OR gates 310 and 410 provide logic high `t_mode` signals to RAM/register blocks 201 and 202, respectively. In response to the logic high `t_mode` (test\_mode) signals, RAM/register blocks 201 and 202 are configured to operate in response to the signals provided by test modules 211 and 212, respectively. (See, Figs. 3 and 4.)

**[0038]** The test bus address/data signal `tb_ad[7:0]` is also set to the first desired write address (WA1) while the `tb_clk` signal has a logic low value. The `tb_ad[7:0]` signal is applied to the D input terminals of flip-flops 311 and 411. The three bits of the "010" `tb_cmd[2:0]` signal are applied to inverting, non-inverting and inverting input terminals, respectively, of AND gates 301 and 401.

**[0039]** The `tb_clk` signal, which is applied to non-inverting input terminals of AND gates 301 and 401, then transitions to a logic high state, thereby causing AND gates 301 and 401 to provide logic high signals to the clock input terminals of flip-flops 311 and 411, respectively. At this time, the first write address WA1 is latched into registers 311 and 411 as the `t_addr_a[7:0]` signal. The first write address WA1 is thereby provided to RAM/register blocks 201 and 202 at this time. The test bus clock signal `tb_clk` then transitions to a logic low state.

**[0040]** The `tb_ad[7:0]` signal is then set equal to a first test data value TD1. This first test data value TD1 can be any desired pattern of 0's and 1's to be written to RAM/register blocks 201-209. The `tb_ad[7:0]` signal is routed directly to RAM/register blocks 201-202 as the `t_din[7:0]` signal.

**[0041]** The test bus byte enable select signal `tb_be_sel[1:0]` is selected to correspond with one of four byte locations in the first write address WA1. In the described example, the



[0044] A second test data value is then written to a second byte location of the first write address WA1 by providing the desired test data value as the tb\_ad[7:0] signal, incrementing the tb\_be\_sel[1:0] signal to a value of "01", and keeping the tb\_cmd[2:0] signal at a value of "100". At the next rising edge of the tb\_clk signal, the decoded tb\_be\_sel[1:0] signal is provided to RAM/register blocks 201 and 202, respectively, as the write enable signals t\_we[3:0] and t\_wea[3:0], respectively.

[0045] Subsequently, the CKA system clock signal transitions to a logic high state, thereby causing the second test data value TD2 to be written to the second byte location of the first write address WA1 in RAM/register block 201, and to the second byte location of the first write address WA1 of the first write port of RAM/register block 202.

[0046] These steps are repeated to write test data values to the third and fourth byte locations of the first write address WA1 in RAM/register blocks 201-209.

[0047] The above-described process is repeated until RAM/register block 201 has been filled with test data values. Note that there are 128 write addresses associated with RAM/register block 201, and only 32 write addresses associated with the first write port of RAM/register block 202. As a result, RAM/register block 202 will be written four times.

[0048] Alternately, test data values can be written to RAM/register block 202 through the second write port of RAM/register block 202. To accomplish this, the test bus command signal tb\_cmd[2:0] is set to a value of "011", while the test bus clock tb\_clk has a logic low value. The test bus address/data signal tb\_ad[7:0] is also set to the desired write address (WB1) while the tb\_clk signal has a logic low value. The tb\_ad[7:0] signal is applied to the D input terminal of flip-flop 412. The three bits of the "011" tb\_cmd[2:0] signal are applied to

inverting, non-inverting and non-inverting input terminals, respectively, of AND gate 402.

[0049] The tb\_clk signal, which is applied to a non-inverting input terminal of AND gate 402, then transitions to a logic high state, thereby causing AND 402 to provide a logic high signal to the clock input terminal of flip-flop 412. At this time, the first write address WB1 is latched into register 412 as the t\_addr\_b[7:0] signal. The first write address WB1 is thereby provided to RAM/register block 202 at this time. The tb\_clk signal then transitions to a logic low state.

[0050] The tb\_ad[7:0] signal is then set equal to a first test data value TD1, and is routed directly to RAM/register block 202 as the t\_din[7:0] signal.

[0051] The test bus byte enable select signal tb\_be\_sel[1:0] is selected to correspond with one of four byte locations in the first write address WB1. The tb\_be\_sel[1:0] signal is routed to decoder 415. In response, decoder 415 provides a corresponding 4-bit byte-enable signal. The 4-bit byte enable signals are routed from decoder 415 to AND gate 408 and 409.

[0052] After the tb\_clk signal transitions to a low value, the tb\_cmd[2:0] signal is set to a value of "101". The three bits of the tb\_cmd[2:0] signal are applied to non-inverting, inverting and non-inverting input terminals, respectively, of AND gate 404. The tb\_clk signal is applied to a non-inverting input terminal of AND gate 404. When the tb\_clk signal transitions to a logic high state, the "101" value of the tb\_cmd[2:0] signal and the logic high value of the tb\_clk signal cause AND gate 404 to provide a logic high value to AND gate 409. As a result, AND gate 409 passes the decoded byte-enable signals from decoder 415 to RAM/register block 202, as the write enable signal t\_web[3:0].

[0053] Subsequently, the CKB system clock signal transitions to a logic high state, thereby causing the first test data value

[0054] After RAM/register blocks 201 and 202 have been written with the desired test data values, the contents of RAM/register blocks 201 and 202 are read out to determine whether these blocks are reliably storing the written test data values. Although the test data values are broadcast to all of the RAM/register blocks during the write operations, each of the RAM/register blocks must be individually accessed during the read operation.

[0056] The tb\_cmd[2:0] signal is then set to a value of "001" while the tb\_clk signal has a logic low value. The three bits of the tb\_cmd[2:0] signal are applied to inverting, inverting and non-inverting input terminals, respectively, of AND gate 304. As a result, the next rising edge of the tb\_clk signal (along with the "001" tb cmd[2:0] signal) causes AND gate 304 to provide a

logic high value to the clock terminal of flip-flop 313. Under these conditions, the logic high value provided by comparator 316 is latched into flip-flop 313, thereby providing a logic high SELECT signal. The logic high SELECT signal is provided to an input terminal of AND gate 305. The tb\_clk signal then returns to a low state.

[0057] The tb\_ad[7:0] signal is then set to the first desired read address, RB1. The tb\_cmd[2:0] signal is then set to a value of "011". The three bits of the tb\_cmd[2:0] signal are applied to inverting, non-inverting and non-inverting input terminals, respectively, of AND gate 302. As a result, the next rising edge of the tb\_clk signal (along with the "011" tb\_cmd[2:0] signal) causes AND gate 302 to provide a logic high value to the clock terminal of flip-flop 312. Under these conditions, the read address RB1 is latched into flip-flop 312, and routed to RAM/register block 201 as the t\_addr\_b[7:0] signal.

[0058] At the next rising edge of the CKB signal, RAM/register block 201 provides a test data value corresponding with the first read address RB1 to multiplexer 331 as the read output signals t\_dout[31:24], t\_dout[23:16], t\_dout[15:8], and t\_dout[7:0].

[0059] The tb\_be\_sel[1:0] signal is selected to correspond with one of four byte locations in the first read address. The tb\_be\_sel[1:0] signal is routed to multiplexer 331. In response, multiplexer 331 provides a corresponding one of the read output signals t\_dout[31:24], t\_dout[23:16], t\_dout[15:8], and t\_dout[7:0]. In the described embodiment, tb\_be\_sel[1:0] signals having values of "11", "10", "01", and "00" will cause multiplexer 331 to pass the read output signals t\_dout[31:24], t\_dout[23:16], t\_dout[15:8], and t\_dout[7:0], respectively. The read output signals routed by multiplexer 331 are provided to tri-state buffer 321.

[0060] At this time, the tb\_cmd[2:0] signal is driven to a value of "111". The three bits of the tb\_cmd[2:0] signal are applied to non-inverting input terminals of AND gate 305. In response to the "111" tb\_cmd[2:0] signal and the logic high SELECT signal, AND gate 305 provides a logic high value to the enable terminal of tri-state buffer 321, thereby enabling tri-state buffer 321. In response, tri-state buffer 321 provides the read output signals routed by multiplexer 331 as the output data signals tb\_data[7:0]. These output data signals tb\_data[7:0] are compared with the test data values previously written to RAM/register block 201, thereby determining whether RAM/register block 201 is reliably storing the written test data values.

[0061] In the described embodiment, the tb\_be\_sel[1:0] signal is cycled through the values of "00", "01", "10" and "11", such that the read data values t\_dout[7:0], t\_dout[15:8], t\_dout[23:16], and t\_dout[31:24] are all read out as the tb\_data[7:0] signal.

[0062] The above-described process is repeated for the other read addresses of RAM/register block 201, until all of the test data values in RAM/register block 201 have been read.

[0063] After the test data values have been read from RAM/register block 201, the test data values can be read from another RAM/register block, such as RAM/register block 202. A similar process is used to read the test data values from RAM/register block 202. However, the process is slightly different because of the dual-port nature of RAM/register block 202. Thus, the tb\_ad[3:0] bits are initially set to a value of "0001", thereby matching the ram\_id[3:0] of RAM/register block 202, and causing comparator 416 to provide a logic high value to the D input terminal of flip-flop 413. The tb\_cmd[2:0] signal is then set to "001", thereby causing flip-flop 413 to latch the logic high value provided by comparator 416 at the next rising

edge of the tb\_clk signal. As a result, flip-flop 413 provides a logic high SELECT signal to AND gates 406 and 407.

[0064] To read test data values from the first port of RAM/register block 202, the tb\_ad[7:0] signal is set to the desired read address, and the tb\_cmd[2:0] signal is set to "010", such that the read address is latched in flip-flop 411 at the next rising edge of the tb\_clk signal. In response, RAM/register block 202 provides the output data values t\_douta[7:0], t\_douta[15:8], t\_douta[23:16] and t\_douta[31:24] from the first read port of RAM/register block 202 to multiplexer 431. The tb\_be\_sel[1:0] signal is selected to cause multiplexer 431 to route a desired one of these output data values to tri-state buffer 421. The tb\_cmd[2:0] signal is then set to a value of "111", thereby causing AND gate 406 to provide a logic high value to enable tri-state buffer 421 at the next rising edge of the tb\_clk signal. In response, tri-state buffer 421 provides the output data value routed by multiplexer 431 as the output data signal tb\_data[7:0].

[0065] To read test data values from the second port of RAM/register block 202, the tb\_ad[7:0] signal is set to the desired read address, and the tb\_cmd[2:0] signal is set to "011", thereby causing the read address to be latched in flip-flop 412 at the next rising edge of the tb\_clk signal. In response, RAM/register block 202 provides the output data values t\_doutb[7:0], t\_doutb[15:8], t\_doutb[23:16] and t\_doutb[31:24] from the second read port of RAM/register block 202 to multiplexer 432. The tb\_be\_sel[1:0] signal is selected to cause multiplexer 432 to route a desired one of these output data values to tri-state buffer 422. The tb\_cmd[2:0] signal is then set to a value of "110", thereby causing AND gate 408 to provide a logic high value to enable tri-state buffer 422 at the next rising edge of the tb\_clk signal. In response, tri-state buffer

422 provides the output data value routed by multiplexer 432 as the output data signal `tb_data[7:0]`.

[0066] In the foregoing manner, test data values can be written and read from the RAM/register blocks of an integrated circuit chip in an efficient manner.

[0067] Note that the signals on test bus 200 can be operated in response to a test clock signal (`tb_clk`), while the RAM/register blocks 201-209 are operated in response to the system clock signals (i.e., the CKA and CKB signals). These clock signals are independent, thereby allowing these clock signals to be different. Because the edges of the first clock signal can be adjusted relative to the edges of the system clock during test mode, the RAM/register blocks 201-209 to be subjected to stress testing, wherein the maximum operating speed of RAM/register blocks 201-209 is determined. For example, the read address can be applied 2 nanosec prior to the CKA signal to test the read setup time, or the `t_we` signal can be applied 2 nanosec prior to the CKA signal to test the minimum write time.

[0068] Although the present invention has been described in connection with several embodiments, it is understood that this invention is not limited to the embodiments disclosed, but is capable of various modifications which would be apparent to one of ordinary skill in the art. For example, the output data bus `tb_data[7:0]` could be combined with the address/data bus `tb_ad[7:0]` in another embodiment of the present invention, thereby resulting in a 14-bit test bus. However, the combined address/data bus would have to be a tri-state bus to facilitate both the input and output of test data values on the same lines. Thus, the invention is limited only by the following claims.